



## Panda 4000s Marine Generator

**The ideal entry level generator -  
easy to install and non-stop energy**

- **High starting capacity...**  
perfect for running a diving compressor or an air conditioner
- **230 V / 50 Hz...**  
for your complete on-board power system
- **Extremely compact and light...**  
more room for other things
- **Super-silent sound insulation capsule...**  
you can relax while the generator runs
- **Innovative Design...**  
easy to install and maintain with all connections on one side
- **Integrated fuel pump**



Panda Generator 4000s

Panda P4-Control Panel



**Fischer Panda**®

Power  
wherever  
you are™

<b>Generator</b>		
Model		<b>Panda 4000s FC PMS</b>
Dimensions (LxWxH)	[mm]	580 x 360 x 545
Weight	[kg]	97
Sound level (7m / 3m / 1m)	[dB]	54 / 64 / 69
Cooling System		Dual circuit - freshwater cooling via heat exchanger
<b>Performance</b>		
Nominal Output	[kW]	3.8 kW
Continuous Output	[kW]	3.5 kW
Voltage Stability	[%]	230 V ± 5%
Frequency Stability	[%]	50 Hz ± 2Hz
<b>Control</b>		
Starter System		electric start
Remote Control Panel		Panda P4 Control
<b>Engine</b>		
Engine Manufacturer		Farymann
Engine Type		18W430
Engine Displacement	[ccm]	298
Speed	[rpm ]	3000



Disclaimer: The information contained here is to the best of our knowledge accurate at the date of publication. All products are subject to continuous development and Fischer Panda GmbH reserves the right to alter technical specifications without prior notice.



Fischer Panda GmbH  
 Otto-Hahn-Str. 32-34 • 33104 Paderborn, Germany  
 Telephone +49 (0) 52 54 / 9202-0 • Telefax +49 (0) 52 54 / 9202-550  
 E-Mail: [info@fischerpanda.de](mailto:info@fischerpanda.de)  
[www.fischerpanda.net](http://www.fischerpanda.net)

Contact your Fischer Panda dealer for more information:

Art.: 71.02.01.013H